

LHT EZ1 WH2002

UNIVERSAL WIRING KIT

Wiring Instructions

You will see a red wire and a white wire with a fuse holder.

Connect these two wires to 12V positive.

The black double wire with the ring connector will connect to 12V negative.

The long white wire with the black stripe also connects to 12V negative.

The wires with bullet plugs are the headlight connections.

The white wire is the positive feed from the relay and the black wire is for negative.

NOTE: On electric vehicles DO NOT USE FRAME GROUND.

Only gas vehicles can use frame ground.

